



GP
ELECTRONICS

DTC124EUA


Digital Transistor

DTC124EUA Digital Transistor(NPN)

Feature

- Built-in bias resistors enable the configuration of an inverter circuit without connecting external input resistors
- The bias resistors consist of thin-film resistors with complete isolation to allow positive biasing of the input. They also have the advantage of almost completely eliminating parasitic effects
- Only the on/off conditions need to be set for operation, making device design easy

Marking: H25







ABSOLUTE MAXIMUM RATINGS ($T_A=25^\circ\text{C}$ unless otherwise noted)


Parameter	Symbol	Value	Unit
Supply Voltage	V_{CC}	50	V
Input Voltage	V_{IN}	-10~+40	V
Output Current	I_C	100	mA
	I_O	30	mA
Power Dissipation	P_D	200	mW
Junction Temperature	T_J	150	°C
Storage Temperature Range	T_{STG}	-55 ~ +150	°C

ELECTRICAL CHARACTERISTICS ($T_A=25^\circ\text{C}$ unless otherwise noted)

Parameter	Symbol	Test Condition	Min	Type	Max	Unit
Input Voltage	$V_{I(off)}$	$V_{CC}=5V, I_O=100\mu\text{A}$			0.5	V
	$V_{I(on)}$	$V_O=0.2V, I_O=5\text{mA}$	3			V
Output Voltage	$V_{O(on)}$	$I_O=10\text{mA}, I_I=0.5\text{mA}$		0.1	0.3	V
Input Current	I_I	$V_I=5V$			0.36	mA
Output Current	$I_O(off)$	$V_{CC}=50V, V_I=0V$			0.5	μA
DC Current Gain	G_I	$V_O=5V, I_O=5\text{mA}$	56			
Input Resistance	R_I		15.4	22	28.6	$\text{k}\Omega$
Resistance Ratio	R_2/R_1		0.8	1	1.2	
Transition Frequency	f_T	$V_O=10V, I_O=5\text{mA}, f=100\text{MHz}$		250		MHz

Typical Characteristics



SOT-323 Package Information


Symbol	Dimensions In Millimeters	
	Min.	Max.
A	1.95	2.35
L	2.00	2.20
E	1.20	1.40
B	1.15	1.35
C	0.30	0.50
L1	0.85	1.15
a	0.20	0.40
P	7°	

Attention:

- GreenPower Electronics reserves the right to improve product design function and reliability without notice.
- Any and all semiconductor products have certain probability to fail or malfunction, which may result in personal injury, death or property damage. Customer are solely responsible for providing adequate safe measures when design their systems.
- GreenPower Electronics products belong to consumer electronics or other civilian electronic products.